

Quick Link: www.fair-rite.com/cb

Low Current

Part Number	✓	Pkg. Size	Impedance (Ω)					Signal Speed	Max DCR (Ω)	Max Current (mA)
			50 MHz	100 MHz ⁺	500 MHz	1000 MHz	1000 MHz ⁺			
2508059007Y0	✓	0805 (2012)	68	90 ±25%	125	107	-	Standard	0.200	300
2508051017Y0	✓	0805 (2012)	75	100 ±25%	134	120	-	Standard	0.200	300
2508051217Y0	✓	0805 (2012)	89	120 ±25%	172	127	-	Standard	0.200	300
2508051817Y0	✓	0805 (2012)	134	180 ±25%	198	111	-	Standard	0.200	300
2508053017Y0	✓	0805 (2012)	216	300 ±25%	161	84	-	Standard	0.250	300
2508056017Y0	✓	0805 (2012)	428	600 ±25%	284	141	-	Standard	0.350	300
2508051027Y0	✓	0805 (2012)	688	1000 ±25%	300	148	-	Standard	0.450	300
2508051527Y0	✓	0805 (2012)	989	1500 ±25%	235	118	-	Standard	0.700	300
2508056007Z0	✓	0805 (2012)	28	60 ±25%	111	122	-	High	0.150	300
2508051217Z0	✓	0805 (2012)	45	120 ±25%	253	191	-	High	0.200	250
2508053017Z0	✓	0805 (2012)	118	300 ±25%	280	139	-	High	0.250	200
2508052027Z0	✓	0805 (2012)	440	2000 ±25%	160	80	-	High	0.400	200
2512063007Y0	✓	1206 (3216)	21	30 ±25%	49	52	-	Standard	0.100	800
2512065007Y0	✓	1206 (3216)	38	50 ±25%	68	67	-	Standard	0.150	800
2512067007Y0	✓	1206 (3216)	53	70 ±25%	101	102	-	Standard	0.150	500
2512069007Y0	✓	1206 (3216)	72	90 ±25%	121	113	-	Standard	0.200	450
2512061017Y0	✓	1206 (3216)	72	100 ±25%	127	86	-	Standard	0.200	450
2512061217Y0	✓	1206 (3216)	87	120 ±25%	151	109	-	Standard	0.200	450
2512063017Y0	✓	1206 (3216)	203	300 ±25%	233	118	-	Standard	0.200	350
2512066017Y0	✓	1206 (3216)	581	600 ±25%	116	67	-	Standard	0.250	350
2512061027Y0	✓	1206 (3216)	784	1000 ±25%	230	117	-	Standard	0.350	350
2512061527Y0	✓	1206 (3216)	1600	1500 ±25%	120	25	-	Standard	0.400	350
2518061017Y0	✓	1806 (4516)	73	100 ±25%	153	155	-	Standard	0.300	400
2518061517Y0	✓	1806 (4516)	110	150 ±25%	205	167	-	Standard	0.500	200